

Project:

Fixture Type: Location:

Contact:

Images:

P8061 SERIES 5IN

5IN LED New Construction And Remodel • Wet location listed PROGRESS LED

Description:

The P8061 is ideal for use in both new construction as well as remodel/retrofit. Light output is comparable to that of a typical 65W incandescent downlight, providing up to 75% energy savings. The P8061 is equipped with both Edison base adapter and quick link connector allowing easy installation in many standard incandescent recessed housings.

Specifications:

- Brushed Nickel finish.
- Diffused polycarbonate lens controls direct glare from the LEDs.
- Easy "Push and Twist" installation with (3) friction spring clips.
- Can be installed in most competitors 5" recessed housings.
- Dimmable to 10% with many Triac/Forward Phase dimmers.
- Suitable for use in IC or NON-IC Applications.
- Provided with quick link for use with E26 Edison Base adapter.
- · This product is not available for sale into the State of California.
- 6" of wire supplied
- ENERGY STAR[®] qualified
- Meets California Title 24 JA8-2016

Performance:


Input Power	10w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW	713/71 (LM-79)
ССТ	3000 K
CRI	90 CRI
Life (hours)	50,000 (L70/TM-21)
EMI/RFI	FCC Title 47, Part 15 Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Wet location listed
	ENERGY STAR® qualified
	Meets California Title 24 JA8-2016




P8061-09-30K

Dimensions:

- (A) Outside Diameter: 6.2"
- (B) Height: 4"
- (C) Inside Diameter: 4.5"
- (D) Light Emitting Surface (LES): 2.75"







P8061 SERIES

5IN LED New Construction And Remodel • Wet location listed PROGRESS LED



Dimming Notes:

P8061 is designed to be compatible with many Triac/Forward Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron AYCL-153P	
Lutron TGCL-153P	
Leviton 6672	
Leviton 6674	
Leviton 6681	

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.